# JEE Main Maths Short Notes Circles

Powered by :







# 1. Circle

A circle is the locus of a point whose distance is constant from a given point around which it moves.

## **Equation of circle**

A circle with center (a, b) and radius r is given as

 $(x + a)^2 + (y + b)^2 = r^2$ 

### 3. The general equation of the circle

Any second order curve can be defined as

Ax<sup>2</sup>+Bxy+Cy<sup>2</sup>+Gx+Hy+D=0

The equation represents a circle on the conditions:

A=C and B=0.

Thus, the general equation of the circle is

$$Ax^2+Ay^2+Dx+Ey+G=0$$

Or

 $x^2+y^2+2gx+2hy+c=0$ 

Rewrite the equation of the circle

 $x^2+y^2+2gx+2hy+c=0$ 

 $x^{2}+y^{2}+2gx+2hy+c+g^{2}+h^{2}=g^{2}+h^{2}$ 

 $(x + g)^2 + (y + h)^2 = g^2 + h^2 - c$ 

The center of the circle is (-g,-h) and the radius of the circle is

$$\sqrt{g^2 + h^2 - c}$$

**Note: For a real circle**  $g^2+h^2-c\geq 0$ 

# 4.Diametric form of a circle

If the endpoints of a diameter to the circle are  $(x_1,y_1)$  and  $(x_2,y_2)$ 



No.1 site & app for JEE, BITSAT, NEET, SSC, Banking & other competitive exams preparation



$$\left(\frac{y-y_1}{x-x_1}\right)\left(\frac{y-y_2}{x-x_2}\right) = -1$$

#### Position of a point w.r.t circle

If S:  $x^2 + y^2 + 2gx + 2hy + c = 0$ 

Let point be  $P(x_1, y_1)$ 

 $S_p: x_1^2 + y_1^2 + 2gx_1 + 2hy_1 + c = 0$ 

If  $S_p > 0$  point lies outside the circle.

If  $S_p = 0$  point lies on the circle.

If  $S_p < 0$  point lies inside the circle.

If the point lies outside the circle, the greatest distance of the point from the circle is

(CP + r) and the least distance of the point from the circle is (CP - r).

#### Parametric equation of the circle

The parametric coordinates of the circle are  $(x_1 + r\cos\theta, y_1 + r\sin\theta)$  where the  $(x_1, y_1)$  is the centre of the circle and r is the radius of the circle, is the angle made by the point from the centre.

The parametric equation is given by

$$\frac{\mathbf{x} - \mathbf{x}_1}{\cos \theta} = \frac{\mathbf{y} - \mathbf{y}_1}{\sin \theta} = \mathbf{r}$$

#### Line and Circle

Solve the equation of circle by substituting any one variable from the equation of the line. A quadratic equation in any on a variable is formed. Evaluate the determinant of the equation.

If the discriminant, D > 0, the line is a secant.

If the discriminant, D=0, the line is a tangent.

If the discriminant, D<0, then the line doesn't touch the circle.

#### Equation of tangent of the circle



#### No.1 site & app

for JEE, BITSAT, NEET, SSC, Banking & other competitive exams preparation





www.gradeup.co At a point (x<sub>1</sub>, y<sub>1</sub>)

Form the equation of tangent by replacing

 $x^2 \rightarrow xx_1$ 

 $y^2 \rightarrow yy_1$ 

 $x \rightarrow (x+x_1)/2$ 

 $y \rightarrow (y+y_1)/2$ 

in the equation of the circle.

#### Slope form

If the equation of the tangent is y=mx + c, where m is the slope of the tangent and c is arbitrary constant, then Slope of the tangent to a circle  $x^2 + y^2 = r^2$  is

$$y = mx \pm a\sqrt{1 + m^2}$$

#### 9.Length of the tangent

If the equation of circle is given as, **S**:  $x^2 + y^2 + 2gx + 2hy + c=0$ , the length of tangent to the point  $P(x_1,y_1)$  is given by

 $L_T = \sqrt{S_P}$ 

Where  $S_p: x_1^2 + y_1^2 + 2gx_1 + 2hy_1 + c$ 

# 10. The equation of chord of a circle when the median of the chord is given.

If the median of the chord is (h, k), then the equation of chord to the circle

S:  $(x + a)^2 + (y + b)^2 = r^2$ 

is

 $xh+yk-r^2=h^2+k^2$ 

or

 $(T=S_P)$ 

# 11. Equation of chord of contact



#### No.1 site & app

for JEE, BITSAT, NEET, SSC, Banking & other competitive exams preparation





The equation of chord from the contact to the circle S:  $(x + a)^2 + (y + b)^2 = r^2$  is

 $xh+yk-r^2=0$ 

### 12. Equation of pair of tangents

If the circle is given as S:  $x^2 + y^2 = r^2$ 

 $S_p: x_1^2 + y_1^2 = r^2$ 

 $T_P: xx_1+yy_1 = r^2$ 

 $SS_P = T_P^2$ 

### 13. Family of circles passing the points of intersection of two circles

If the circle S' and S'' are intersecting, the family of circles that can be formed from the point of contacts S' and S'' is

 $S' + \lambda S'' = 0$ 

### 14. Family of circles passing the points of intersection of a circle and a line

If the circle S and line L are intersecting, the family of circles that can be formed from the point of contacts S and L is

#### **Common tangent to two circles**


There are two types of common tangents to two circles,

Internal common tangent

External common tangent








#### 16. Position of circles and the number of common tangents

Let  $C_1$  and  $C_2$  denote the centre of the circles,  $r_1 \& r_2$  be the radii of the circles and  $C_1C_2$  be the distance between the centres.

(a) If  $C_1C_2 > r_1 + r_2$ 

There are 4 common tangents




(b) If  $C_1C_2 = r_1 + r_2$ 



#### No.1 site & app


for JEE, BITSAT, NEET, SSC, Banking & other competitive exams preparation





There are 3 common tangents.

(c) If  $|r_1 - r_2| < C_1 C_2 < r_1 + r_2$ 



There are 2 common tangents.

(d) If  $C_1C_2 = |r_1 - r_2|$ 



There is one common tangent.

(e) If  $C_1C_2 < |r_1 - r_2|$ 



No.1 site & app for JEE, BITSAT, NEET, SSC, Banking & other competitive exams preparation



$$\bigcirc$$

There is no common tangent.

### **17.** Length of common tangent

#### (a) External tangent

$$L_{ET} = \sqrt{(C_1 C_2)^2 - (r_1 - r_2)^2}$$

### (b) Internal tangent

$$L_{_{\rm IT}}=\sqrt{\left(C_{_{\rm I}}C_{_{\rm 2}}\right)^2-\left(r_{_{\rm I}}+r_{_{\rm 2}}\right)^2}$$

### 18. The condition of orthogonality of two circles

Two circles intersect each other at 90° when

 $2g_1g_2 + 2f_1f_2 = c_1 + c_2$ 

Subscribe to YouTube Channel for JEE Main

#### All the best! Team Gradeup

All About JEE Main Examination: https://gradeup.co/engineering-entrance-exams/jee-main

Download Gradeup, the best IIT JEE Preparation App



No.1 site & app for JEE, BITSAT, NEET, SSC, Banking & other competitive exams preparation



# JEE, NEET, GATE, SSC, Banking & other Competitive Exams

- Based on Latest Exam Pattern
- NTA based JEE Preparation

ANDF

- Get your doubt resolved by mentors
- Practice questions and get detailed solutions
- Previous year paper detailed solution

	Current Electricity and E	
	battery B. of emf E, a resistance R, and an	
	s Mm	ľ
OID APP ON		
oogle <sup>®</sup> play	The current f	
	is closed is	
	E/R E/R	